

DOOR TRIGGER DIODE ISOLATION ON 95-97 BLAZER, JIMMY, AND BRAVADA

NOTE:



When doing security on 95-97 Chevy Blazers, Oldsmobile Bravadas and GMC Jimmys, the door trigger wire catches all doors, but there is a dome light delay. To keep the alarm from reading the delay, place a diode in-line on the white door trigger wire with the anode towards the keyless module. Attach your door trigger wire to the cathode side of the diode. On non-keyless models there is a module with 5 wires located where the keyless normally resides. The white wire there catches only the front two doors. To catch the rear doors use the white wire at the driver's side rear pin switch.

